



BSD-L7NHA010U-2

EtherCAT servo drive

- EtherCAT slave node
- Input voltage 1- or 3-phase 200-240 VAC
- Output power 800 W
- Output current 6.75 A
- Motor autodetect and adapt
- Universal encoder
- STO safety

Facts

General description

Article number	71464
Warranty	1 year

Mechanical

IP Class	IP20
Size	169x58x197 mm
Weight	1.5 kg

Ambient conditions

Environment	Indoors in an area free from corrosive or combustible gases, liquids, or dust.
Humidity	90% RH or less (no condensation)
Temperature range	Operating: 0 to 50 C°, Storage: -20 to +65 C°

Input ratings

Control supply voltage	200 to 230VAC
Mains supply voltage	1- or 3-phase 200-230VAC
Overload capacity	300 % for 3 s
Supply frequency	50 to 60 Hz
Voltage fluctuations	-15 to +10%

Output ratings

Rated power	800 W
-------------	-------

Encoder

Encoder type	Quadrature(Incremental) BiSS-B, BiSS-C(Absolute, Incremental) Tamagawa Serial(Absolute, Incremental) EnDat 2.2 Sinusoidal, Analog Hall
--------------	--

Regenerative

Built-in brake resistor	Yes
Built-in brake transistor	Yes

Dynamic braking

Dynamic brake	Yes
---------------	-----

Control specifications

Control modes	Profile Position Mode Profile Velocity Mode Profile Torque Mode Cyclic Synchronous Position Mode Cyclic Synchronous Velocity Mode Cyclic Synchronous Torque Mode Homing Mode
Frequency response	Maximum 1Khz or above (when using 19-bit serial encoder)
Speed control range	Maximum 1:5000
Torque control repeatability	Within $\pm 1\%$
Tuning modes	On line auto gain tuning Resonance filters Vibration supression

Control terminals

Analog inputs	Input voltage range : -10[V] ~ +10[V] Function : Analog torque limit Total 1 input channel (not allocable)
Analog outputs	Total 2 input channels (allocable)
Digital inputs	Input Voltage range : DC 12[V] ~ DC 24[V] Total 8 input channels (allocable) The listed 15 functions can be used selectively for assignment. (*POT, *NOT, *HOME, *STOP, *PCON, *GAIN2, *P_CL, *N_CL, PROBE1, PROBE2, EMG, A_RST, SVON, LVSF1, LVSF2) Note) * Basic allocation signal
Digital transistor outputs	Signal rating: DC 24[V] $\pm 10\%$, 120[mA] Total 4 input channels (allocable) The listed 11 functions can be used selectively for assignment. (*BRAKE $\pm$, *ALARM $\pm$, *READY $\pm$, *ZSPD $\pm$, INPOS $\pm$, TLMT $\pm$, VLMT $\pm$, INSPD $\pm$, WARN $\pm$, TGON $\pm$, INPOS2 $\pm$) Note) * Basic allocation signal

Safety

Safety	2 input channels (STO1, STO2), 1 output channel (EDM)
--------	---

Communication

EtherCAT	Yes
Modbus RTU	No
Communication connector	RJ45 (1 input, 1 output)
DC-clock cycle time	250 µs

Standard compliances

Applied directives	EMC EN 61800-3:2004 + A1:2012 LVD: EN 61800-5-1:2007 STO Safety: EN 61508-1:2010, EN 61508-2:2010, EN 61508-3:2010, EN 61508-4:2010, EN ISO 13849-1:2008/AC, SIL 2, Category 3 PLd, EN 61800-5-2:2007
--------------------	---

People & Technology. Connected.

We are a people company. Our experienced, skilled and passionate people empower you to meet your challenges through best-in-class, user-friendly solutions. We are a technology company. We help you optimize processes through our software, hardware and services, and through our support. Connecting people and technologies gives you the means to accomplish your goals and ambitions, and gain a competitive edge in today's digitalized world.

Visiting address HQ: Stora Varvsgatan 13a

SE - 211 75 Malmö, SWEDEN

+46 40 35 86 00 (tel:+46 40 35 86 00)

info@beijerelectronics.com (mailto:info@beijerelectronics.com)